



- Reliable stable switch and dimming control function, control range $\geq 20M$.
- Switch on/off of lightings slowly, without any flash, meet the comfort of human eyes.
- Dimming range 0.1-100%.
- Enable to control 4 zones separately, And dim or ON/OFF 3 zones at same time ,each zone can be set endless receivers, each receiver maximally be controlled by 8 different remotes.

Picture		Brief introduction of buttons	
Operation Voltage	Operation Frequency	<p><i>Note : This remote controls 4 zones (areas) receiver, each zone can pair with countless receivers. 1 receiver can be paired by max 8 different remote controls.</i></p>	
3V(CR2025 battery)	868MHz		
Size		Operation	
		<p>Note: Before the first use, please remove the protective film on the battery.</p> <ol style="list-style-type: none"> Pair with RF receivers: <p>Turn on RF remote → Click "Learning Key" on RF receiver → Click I or O of any zone , led lights flicker twice means well paired</p> Play the remote after pairing: <p>Turn on RF remote → Touch any buttons to do the controlling</p> Save color/scene: <p>Turn on RF remote → select a color → Hold S1/S2 until led lights flicker</p> Call up the saved: <p>Turn on RF remote → Click S1/S2 button</p> How to delete the pairing: <p>Power on the RF receiver, hold the "Learning Key" over 3 seconds until connected led lights flicker twice means well deleted.</p> 	